



LOL-DOW-0400

Model No	LOL-DOW-0400
Application	Downlight
Name	Copper Pendant Light
Description	
• • • • • • • • • • • • • • • • • • • •	oer pendant light can be hung uitable elevated garden features, que ambience.
Power Input	12V
Lamp details	MR11
Power Usage	2W
Beam Angles	Narrow, Medium or Wide
Colour Temperature	TBA
Lumen	TBA
CRI	TBA
Dimming System	TBA
IP	
Finish	Non Corrosive Copper
Mounting	Hanging with corrosion resistant chain or suitable hanging wire
Dimensions	60Ø x 235H
Product Notes	
CRI, Lumen and dimming	protocals depend on the type of



lamp installed. Call to discuss.

Please contact Light on Landscape to confirm the availability and current specifications of this luminaire.

Installation

Light on Landscape strongly recommend that all luminaires be correctly installed and maintained. Failure to do so will result in the voiding of the manufacturer's warranty and the reduced efficiency, performance and life of the fixture. To eliminate voltage drop, we advise that the recommended UV stabilized cable and run lengths are used, along with soldered joins, heat shrink connectors and quality lamps.

